lofree

产品规格

电芯容量：	800mAh
D P I ：	800/1200(默认)/1600/2400/3600
输入电压：	5V ⎓ 1A
蓝 牙 名 ：	Maus@LOFREE
尺 寸：	102.5 x 62.7 x 35mm
重 量：	约 98 g
按 钮 数 ：	8个
蓝牙版本：	蓝牙4.0
两种连接方式：	蓝牙 /2.4G
2.4G Dongle名：	Maus 2.4G@LOFREE
适用设备/系统：	Macbook/ iMac 一体机 / Windows 电脑

系统适用性备注：

❶ 蓝牙连接下，仅支持Windows8及以上的系统，Windows7及以下系统请使用2.4G USB连接使用。

❷ 苹果系统电脑在2.4G USB连接下不支持手势功能。

产品图解



按键定义：

❶ **电源开关：**
拨动开关，ON为开机，OFF为关机。

❷ **蓝牙/2.4G切换开关：**
拨动开关，可在蓝牙连接和2.4G无线连接中切换。

❸ **DPI键：**
DPI切换：短按切换DPI值，可在五档DPI（800/1200/1600/2400/3600）中循环切换。

❹ **滚轮+中键：**实现功能。

❺ **左右按键：**实现功能。

❻ **指示灯：**用于显示充电电量多少的状态，以及蓝牙连接和切换DPI值时的灯光指示。

❼ **侧滚轮键：**
1. 将滚轮向前滚动：放大图片；将滚轮向后滚动：缩小图片
2. 按住侧滚轮键将鼠标前后左右滑动，即进入手势功能，具体功能定义如下表展示：

Windows8及以上系统		苹果系统
按压前滑	上页/Page Up	图片向上拖动
按压后滑	下页/Page Down	图片向下拖动
按压左滑	多级文件下的后退功能	图片向左拖动
按压右滑	多级文件下的前进功能	图片向右拖动

❽ **侧按键：**
按住侧按键将鼠标前后左右滑动，即进入手势功能，具体功能定义如下表展示：

Windows8及以上系统		苹果系统
按压前滑	多任务界面	任务控制
按压后滑	显示桌面	调度中心

Windows8及以上系统		苹果系统
按压左滑	左跳转/快速切换任务	向左切换全屏应用
按压右滑	右跳转/快速切换任务	向右切换全屏应用

❾ **2.4G接收器仓：**
1. 拉开鼠标侧面的硅胶塞，取出2.4G接收器。
2. 将接收器插入设备的USB接口。



基本操作

❶ **充电**
使用标配的USB线对产品进行充电。电量低于3.5V时，低压报警（红 色灯每1秒快闪1次，不操作后闪10次后灯灭）；低压关机，红灯以3Hz频率快闪10次后关机；充电时红灯亮起；充满后灭。

❷ **电源开关：**
在鼠标底部有ON/OFF拨动开关，拨至ON档为开机，拨至OFF档为关机。不使用时请将开关拨至OFF档，以节省电量。

❸ **两种连接方式：**
蓝牙连接：

A **首次连接：**将鼠标底部切换开关拨至蓝牙模式，长按DPI键3秒进入蓝牙模式，此时蓝牙灯为蓝色闪烁状态，打开电脑搜索蓝牙Maus@LOFREE，连接成功后蓝牙灯常亮3秒后关闭。

B **回连：**连接上电脑以后，下次再使用只需要开机即可，不需要重复连接。如果需要连接另一台电脑，使用首次连接方式即可。

2.4G无线连接：
将鼠标底部切换开关拨至2.4G模式，将无线2.4G接收器插入电脑，即可直接使用。
如果无法连接或者更换新的USB接收器，长按DPI键3秒（或者同时按左中右键3秒）对码后，然后再将无线USB插入电脑，即可正常使用。

❹ **五档DPI切换方式：**
本产品DPI一共有五档：800/1200（默认）/1600/2400/3600。用户可以根据个人习惯进行选择。短按DPI键一次即可按照顺序切换档位，切换到第几档，指示灯绿灯就会相应的闪烁几下。

❺ **睡眠与唤醒方式：**
产品无操作状态下，3秒进入一级睡眠，30分钟进入二级睡眠，移动鼠标即可唤醒。

著片蓝牙鼠标有害物质申明

Component 部件成分	有害物质					
	铅 (Pb)	汞 (Hg)	鎘 (Cd)	六價鉻 (Cr6+)	多溴聯苯 (PBBs)	多溴二苯醚 (PBDEs)
Plastic 塑料	○	○	○	○	○	○
Metal 金属	○	○	○	○	○	○
PCB 电路板	○	○	○	○	○	○
Electronic materials 电子料	○	○	○	○	○	○

Component 部件成分	有害物质					
	铅 (Pb)	汞 (Hg)	鎘 (Cd)	六價鉻 (Cr6+)	多溴聯苯 (PBBs)	多溴二苯醚 (PBDEs)
Leading wire 内部线	○	○	○	○	○	○
Label 标签	○	○	○	○	○	○
Silvery solder 银色焊锡	○	○	○	○	○	○
cushion 垫子	○	○	○	○	○	○
Transparent glass 透明玻璃	○	○	○	○	○	○

依据欧盟指令2011/65/EU及其修订指令进行判定。

O: 表示该有害物质在该部件所有均质材料中的含量均在GB/T26572定的限量要求以下。

X: 表示该有害物质至少在该部件的某一均质材料中的含量超出GB/T26572规定的限量要求。

Product

Battery Capacity:	800mAh
DPI Specification:	800/1200 (default)/1600/2400/3600
Input voltage:	5V ⎓ 1A
Bluetooth Name:	Maus@LOFREE
Dimensions:	102.5×62.7×35mm
Weight:	Approximately 98g
Number of Buttons:	8

Bluetooth:	Bluetooth 4.0
Dual Connectivity:	Bluetooth & 2.4G
2.4G Dongle Name:	Maus 2.4G@LOFREE

Compatible with Device/System: Macbook/ iMac/ Windows PC/ Android

Compatibility notes:

❶ Bluetooth mode is only available for Windows 8 and above system. For Windows 7 or older versions, please use 2.4G USB connection.

❷ Gesture control is not available for Mac OS via 2.4G wireless USB connection.

Product Illustration



Button Functionalities:

❶ **On/Off Button:** Swipe to turn on and off.

❷ **Bluetooth and 2.4G USB Button:** Swipe to turn on and switch between Bluetooth and 2.4G mode.

❸ **DPI Button:**

A **DPI Switching:** Quick presses to switch between 5 DPI levels (800/1200/1600/2400/3600).

B **Bluetooth Connectivity:** Turn on the Bluetooth button at the bottom of the mouse. Hold the DPI button for 3 seconds to enter Bluetooth mode. A blue will LED blink when pairing. The light will stay on for 3 seconds and turn off when successfully paired.

C **2.4G Connectivity:** Switch from Bluetooth to the 2.4G mode with the button on the bottom of the mouse. Plug the USB receiver into your computer' s USB port. If it fails to connect, unplug the USB receiver and hold the DPI button for 3 seconds, then plug the USB receiver into your computer again.

❹ **Scroll Wheel & Middle Button:** Standard functions.

❺ **Left/ Right Button:** Standard functions.

❻ **LED Indicator:** displays the battery status, Bluetooth connectivity status, and the DPI level.

❼ **Side Wheel Scroll:**

A Scroll back and forth to zoom in/out of the image.

B Press the side scroll and move the mouse in a circular motion to enter gesture control.

Windows 8 or latest versions		Apple OS
Hold and Scroll Forward	Page up	Drag the image to the top
Hold and Scroll Backward	Page down	Drag the image to the bottom
Hold and Scroll to the Left	Go back	Drag the image to the left
Hold and Scroll to the Right	Go forward	Drag the image to the right

❽ **Side Button:**
Press the side button and move the mouse in a circular motion to enter gesture control; the specific functions are shown as below.

Windows 8 or latest versions		Apple OS
Hold and Scroll Forward	Multi-task interfaces	Mission Control
Hold and Scroll Backward	Go back to desktop	Launchpad
Hold and Scroll to the Left	Go to previous page	Access to fullscreen
Hold and Scroll to the Right	Go to next page.	Access to fullscreen

❾ **2.4G receiver compartment:**
1. Pull the silicone plug on the side of the mouse and take out the 2.4G receiver.
2. Insert the receiver into the USB port of the device.

Basic Operation

❶ **Charging**
Charge the device with the USB cable provided. When the battery voltage drops below 3.5V,low battery alert will flash in red once every second. If the mouse is inactive, the light will flash 10 times then automatically turn off. When the mouse is being charged, the red LED stays on, it will turn off when fully charged.

❷ **Power On/Off:**
The bottom of the mouse features a power button, switch it to "On" to turn it on and "OFF" to turn it off. Please turn it off if not using to save battery life.

❸ **Dual Connectivity:**

lofree

深圳市洛斐客文化有限公司
Shenzhen Lofree Culture Co., Ltd.
深圳市宝安区西乡街道龙洞路1065号F518时尚创意园F4栋201
201-F4, F518 Idea Land, 1065 Bao Yuan Road, Shenzhen

服务热线：4006002083
www.lofree.com.cn　　www.lofree.co
lofree.co　lofreeco　lofree.co

Bluetooth Connectivity:

A **Initial Pairing:** Turn on the Bluetooth button on the bottom of the mouse. Hold the DPI button for 3 seconds to enter Bluetooth mode. A blue LED will appear when pairing. Search for: "Maus@LOFREE" on your computer. The blue light will stay on for 3 seconds when successfully paired.

B **Subsequent Pairing:** Simply turn on your computer. There is no need to repeat the initial pairing steps unless you would like to pair with other devices.

2.4G Wireless Connectivity:
Switch from Bluetooth mode to 2.4G with the button on the bottom of the mouse. Plug the USB receiver into the USB port on your computer.
If it fails to connect, unplug the USB receiver and hold the DPI button for 3 seconds. Then, plug the USB receiver into your computer again.

❹ **Switching Between the 5 Adjustable DPI:**
This product features 5 DPI levels:
800/1200 (default)/1600/2400/3600. Users can choose between them according to their preferences. Quick press the DPI button to switch between the levels, a green LED will flash between switches.

❺ **Sleep and Wake Up Mode:**
After 3 seconds of inactivity, Maus will enter Sleep Mode I. After 30 minutes of inactivity, it will enter Sleep Mode II. To wake the mouse from Sleep Mode, simply move it.

製品仕様

セル容量:800mAh
DPI:800/1200(default)/1600/2400/3600
入力電圧: 5V⎓1A
Bluetooth名:Maus@LOFREE
サイズ:102.5x62.7x35mm
重量:約98g
ボタン数:8
Bluetoothバージョン:4.0
2種類の接続方法:Bluetooth/2.4GHz
2.4GHzドングル名:Maus 2.4G@LOFREE
対応機種/システム:Macbook/Mac All-in-One/Windows パソコンシステム適用性：
1.Bluetooth接続でWindows 8以上のシステムのみサポートします。
2.Windows7以下のシステムは2.4GHz接続を使用してください。
3.Macパソコンは、2.4GHz接続でジェスチャー機能をサポートしません。

ダイアグラム：



各部のはたらき

❶ **電源スイッチ：**
マウス本体の電源をON・OFFします。。

❷ **Bluetooth/2.4Ghzスイッチ：**
Bluetooth接続と2.4Ghzワイヤレス接続を切替できます。

❸ **3DPIキー：**
DPIスイッチ：短押しで分解能を800dpi→1200dpi→1600dpi→2400dpi→3600dpiに切り替えることができます。

❹ **スクロールボタン：**一般機能。

❺ **左右ボタン：**一般機能。

❻ **LEDインジケーター：**
インジケーター状態、Bluetooth接続状態、DPIレベルを表示。

❼ **サイドホイールスクロール：**
前後にスクロールして画像を拡大・縮小します。
サイドスクロールを押しながらマウス前後左右に動かすと、ジェスチャー機能を入力します。具体的な機能定義は以下の表のとおりです：

Windows8以上		Apple OS
押しながら前方にスクロール	ページアップ	画像を上にドラッグ
押しながら後方にスクロール	ページダウン	画像を下にドラッグ
押しながら左へスクロール	戻る	画像を左にドラッグ
押しながら右へスクロール	進む	画像を右にドラッグ

❽ **サイドボタン：**
サイドボタンを押しながらマウス前後左右に動かすと、ジェスチャー機能を入力します。具体的な機能定義は以下の表のとおりです：

Windows8以上		Apple OS
押しながら前方にスクロール	マルチタスクインターフェース	画像を上にドラッグ
押しながら後方にスクロール	デスクトップに戻る	画像を下にドラッグ
押しながら左へスクロール	前のページへ	フルスクリーンへ
押しながら右へスクロール	次のページへ	フルスクリーンへ

❾ **レシーバー収納スロット**
1. マウス側面のシリコンプラグを引き抜き、2.4Ghzレシーバーを取り出す。
2. レシーバーをデバイスのUSBポートに挿入する。

操作方法

❶ **充電**
付属のUSBケーブルでデバイスを充電してください。バッテリー電圧が3.5Vを下回ると、低バッテリー警告が赤色で1秒に1回点滅します。電源が切れるまで、インジケーターが赤色で3HZの周波数で10回点滅します。充電中はLEDインジケーターが点灯し、満充電になると消灯します。

❷ **電源スイッチ。**
マウス底部にON/OFFトグルスイッチがあり、ONにすると電源が入り、OFFにすると電源が切れます。使用しないときは、電力を節約するために、スイッチをオフにしてください。

❸ **二つの接続方式：**
Bluetooth接続：
初めての接続：マウス下部のスイッチをBluetoothモードに切り替え、DPIスイッチを3秒間押してBluetoothモードにします。この際にインジケーターが青色で点滅します。
パソコンでBluetooth名「Maus@LOFREE」を検索し、接続に成功するとインジケーターが3秒間点灯したら消灯します。
再接続：パソコンに接続した後、次に使用するときは電源を入れるだけで、別のパソコンに接続すると、初めての接続方法をご参照ください。
2.4Ghz接続：
マウス下部のスイッチを2.4Ghzモードに切り替え、パソコンにレシーバーを接続し、マウスは使えるようになります。
接続に失敗した場合は、レシーバーを抜き、DPIボタンを3秒間押したままにして、再度パソコンにレシーバーを接続してください。

❹ **5段階のDPI切り替え：**
本製品は、800/1200（デフォルト）/1600/2400/3600の5つのDPIレベルを備えています。DPIキーを短く押すことで順番にギアを切り替えることができ、それに応じてインジケーターが緑色で数回点滅します。

❺ **スリープとウェイクモード。**
無操作状態、3秒で第１段階のスリープモードに入り、30分で第2段階のスリープモードに入り、マウスを動かすとスリープモードが解除されます。

製品に含まれる有害物質の名称と含有量：

部品構成	有害物質					
	鉛 (Pb)	水銀 (Hg)	カドミウム (Cd)	六価クロム (Cr6+)	ポリ臭化ビフェニル (PBB)	ポリ臭化ジフェニルエーテル (PBDE)
プラスチック	○	○	○	○	○	○
金属	○	○	○	○	○	○
プリント基板	○	○	○	○	○	○
電子材料	○	○	○	○	○	○
リード線	○	○	○	○	○	○
ラベル	○	○	○	○	○	○
銀ロウ	○	○	○	○	○	○
クッション	○	○	○	○	○	○
透明ガラス	○	○	○	○	○	○

本表は、EU指令2011/65/EUに基づいて作成されています。
○当該部品のすべての均質材料中の有害物質の含有量がGB/T26572で規定された制限要件未満である
X:少なくとも当該部品のある均質材料中の当該有害物質の含有量がGB/T26572で規定された制限要件を超えている

MAUS

著片蓝牙鼠标

EP115 Bluetooth Mouse