UNIVERSAL REMOTE

INSTRUCTIONS

UNIVERSAL REMOTE

- English
- Italiano
- Español
- Português

English.....1
Italiano.....7
Spanish.....13
Portuguese.....19
Code Form.....25
TV.....25
DVR/VCR.....41
DVD.....44
CD.....49
SAT.....51
HDD-DVR.....62
DVD-R.....64
Decoder Cable.....65
ASDL (BROADBAND) DTV Receiver.....66
TV / VCR (COMBOS).....66
TV / DVD (COMBOS).....67
DVD / VCR (COMBOS).....68
HTIB.....69
DVB-T.....70
Auxiliary Set-Top Soxes.....71
Picture Frame.....72
AUX.....72
Media Center PC.....74
Home Auto mation.....74

MARANTZ	0727
MEDION	0841.0775.0776
MICROMAXX	0841.0775.0776
MICROSTAR	0841.0775.0776
NAD	0735.0736.0737.0738.0799.0800
NUVO	0862.0863.0864.0865
ONKYO	0785.0792.0793.0826
PHILIPS	0734.0846.0727
PRO2	0841.0775.0776
SANSUI	0727
SCHNEIDER	0791
SHERWOOD	0782
SONY	0739.0740.0755.0757.0758.0759.0760
TCM	0841.0775.0776.0806
TEAC	0794.0796
TECHNICS	0764.0777.0788
TEVION	0775.0776.0815.0817.0841
THEORIE & ANWENDING	0805
THOMSON	0842.0766
XANTECH	0867
YAMAHA	0883.0882.0839.0838.0724.0752.0770.0771.0772

Audio Tape Players

AIWA	0790
DENON	0780
GRUNDIG	0729.0698
HARMON KARDON	0681
KENWOOD	0761
MAGNAVOX	0729
MARANTZ	0729
NAD	0799
ONKYO	0784
PHILIPS	0729
SANSUI	0729
SHERWOOD	0783
SONY	0754.0755.0756
TEAC	0794
TECHNICS	0764.0777.0786
THOMSON	0842
YAMAHA	0724.0772

MINI Systems

AIWA	0773.0774
CYBERCOM	0852.0858.0704.0745.0808.0810.0820.0819
CYBERMAXX	0852.0858.0704.0745.0808.0810.0811.0812.0820.0819
CYTRON	0852.0858.0704.0745.0808.0810.0811.0812.0820.0819
DUAL	0852.0858.0704.0745.0797.0820.0819
E-BENCH	0811
ELTA	0693.0745
GRUNDIG	0707
INSIGNIA	0731
INTERTRONIC	0811
LIFE	0879.0823.0811
LIFETEC	0879.0823.0852.0858.0704.0745.0808.0810.0811.0812.0820.0819
MEDION	0879.0823.0731.0728.0852.0858.0704.0745.0808.0810.0811.0812.0820.0819
MICROMAXX	0852.0858.0704.0745.0808.0810.0811.0812.0820.0819
MICROSTAR	0852.0858.0704.0745.0808.0810.0811.0812.0820.0819
PIONEER	0753
PRO2	0852.0858.0704.0745.0808.0810.0811.0812.0820.0819
SAMSUNG	0768
SHARP	0768
SILVERCREST	0828.0811.0829.0868
SONY	0741
TCM	0879.0880.0852.0858.0704.0745.0808.0810.0811.0820.0819.0694.0823.0824.0825
TEVION	0879.0823.0852.0858.0704.0745.0808.0810.0811.0812.0820.0819.0821.0822

A MANUALLY INPUT THE CORRESPONDING CODE

1. Turn on the household appliances you want to control (such as TV, STB, DVD).
2. Look up the code list for the code corresponding to the brand of the household appliances you want to control. For example, if the brand of your household appliances is "**AKAI**", then the first code will be **5012**.

CODE

AKAI 5012.5055.5060.5067.5093.5094.5095.5102.5109.2017.2020.2025.2195.220

3. Press the device category key (such as "**TV**" key), and the indicator light will twinkle once
4. Press on the "SETUP"(**SET**) key until the indicator light lights and keeps shining; input successively the four-digit code you found. Note: when you input one-digit number, the indicator light will twinkle once. When you finish your inputting, the indicator light will quench.
5. Check whether each function key of the remote control operates normally, if it does, it represents that the corresponding setting is successful; if some of the function keys don't operate normally, please repeat procedure 4 and input other code of the corresponding brand

HAUPPAUGE	0482
HB	1011.1211.1213.0476
HITACHI	1262.0526
HOMECAST	0476
HUMAX	0651
INTERSTAR	0476
JEPSSEN	0476
JVC	0526
KATHREIN	1197
LABGEAR	0513
LASAT	1156
LDCOM	0451
LIFETEC	0645.0650
LOGIK	1263
MARMITEK OCTOPUS	0655
MATSUI	0649.0526.0451
MEDION	0645.0650
MICO	1135
MICROMAXX	0645.0650
MICROSTAR	0645.0650
NOKIA	0519.0531
NOOS	1183
OCEANIC	1011
OGGLE	1136
ON DIGITAL	0527.0531.0620
OPTEX	0656
PACE	0453.0527
PACIFIC	0526
PANASONIC	0072.0403
PHILIPS	0600
PIONEER	0457.0620
PREMIERE	0600.0519
PRO2	0645.0650
REBOX	0476
SAGEM	0448.1143
SCHAUB LORENZ	1011.1211.1212.1213.0476
SCHWAIGER	1156.1229.1173.0630
SHARP	0059
SKARDIN	0656
SKYMASTER	1166.1165.1164.1163.1140.0656.0412.0636.1380.1387.1160.1383
SMART	1247.1245.1242.1165.1133
SMELECTRONIC	0412.0656.1165.1163.1164
SONY	0447
TCM	1413.1017.1119
TECHNIKA	1262
TECHNISAT	1218
TECHNOTREND	1173
TELEVES	0476
TEVION	0645.0650
THOMSON	0427.0532
TOPFIELD	1204.0506
TOP-UP TV	0527.0531.0657
TVONICS	1263
WHARFEDALE	1262
WORLDSAT	0476
YUNG FU	1166

Auxiliary Set-Top Soxes

Web & Computer TV

BUSH	0039
CYBERLINK	1101
GERICOM	0443
HAUPPAUGE	0482
HAUPPAUGE	1198
NOW TV	1186
PACKARD BELL	1101
PANASONIC	0542
PINNACLE	1199.1201.1202
PREMIERE	0542

C FULL-AUTOMATIC SEARCHING FOR CODE

1. Turn on the household appliances you want to control (such as TV, STB, DVD)
2. Press the device category key (such as **TV**, SAT, DVD), and the indicator light will twinkle once
3. Press on the "SETUP"(**SET**) key until the indicator light lights and keeps shining
4. Point the remote control towards the infrared reception window of the equipment you're going to control, press "Channel +" (**CH+**/P+), enter the status for automatic search as the indicator flashes rapidly, the remote transmits a set of codes every second. When the device responds, press "**OK**" key quickly and exit search status.

Attention: If the equipment doesn't have "CH+"(P+) function, you may use the "**PLAY**" key or the "**POWER**" key instead, and when the equipment's status begin to change, press "OK" key to exit.

5. Check whether every function keys of the remote control work normally, if it does, the setting is successful; if not, please repeat procedure 3-4.

HTIB

Home Cinema Systems operate with either a single DVD code or some require both DVD & AUDIO codes.

1. Press the category key of the equipment you want to inquire (such as **TV**, SAT, DVD), and the indicator light will twinkle once
2. Press on the "SETUP"(**SET**) key until the indicator light lights and keeps shining
3. Press the "SETUP"(**SET**) key once again, and after twinkling once, the indicator light will keeps shining
4. Press number **0-9** successively until the indicator light twinkles once, and the current number is just the first-digit number of the code
5. Repeat procedure 4, find out the 2nd-digital, 3rd-digital and 4th-digital number successively, and when you find out the 4th-digit number, the indicator light will quench

DELETE ALL THE LEARNED KEYS OF CERTAIN EQUIPMENT

1. Press the device category key you want to delete (such as **TV**, SAT, DVD), and the indicator light will twinkle once
2. Press on the "SETUP"(**SET**) key until the indicator light lights and keeps shining
3. Press the "**LEARN**" key twice, the indicator flashes once (or enter code "**9981**");
4. Press the number "**1**" key. All the learned keys of the equipment will be deleted

DELETE THE LEARNING OBJECTS OF ALL EQUIPMENTS

1. Press on the "SETUP"(**SET**) key until the indicator light lights and keeps shining
2. Press the "**LEARN**" key twice, the indicator flashes once (or enter code "**9981**");
3. Press the number "**0**" key. The learning objects of all equipments will be deleted

VOLUME CONTROL PENETRATING FUNCTION SETTING

By setting this function, you may, even if then the current controlled equipment is not TV, still be able to control TV equipment under the volume of TV control mode.

1. Press on the "SETUP"(**SET**) key until the indicator light lights and keeps shining
2. Press the "V+"(**VOL+**) key, and the indicator light lights and keeps shining
3. Press the key representing certain device (eg. **TV**, SAT, DVD, etc) to get through, the indicator flashes and goes out, and the setting is finished.

CANCEL VOLUME CONTROL PENETRATING FUNCTION

1. Press the corresponding device category key (such as **TV**, SAT, DVD), and the indicator light will twinkle once
2. Press on the "SETUP"(**SET**) key until the indicator light lights and keeps shining
3. Press the "V-"(**VOL-**) key, and the indicator light will quench after twinkling twice, the volume control penetrating function being cancelled.

MANUALE D'USO

Italiano

Grazie per aver acquistato questo telecomando, dopo una corretta installazione, e' in grado di supportare i seguenti tipi di dispositivo

Tasti dispositivo	Tipi di dispositivi inclusi
TV	TV / DTV Receiver / TDT
SAT	SAT / Decoder Cable / DVB-T
DVD	DVD / DVD-R
AUX	AUX / Audio / Amplifiers / Tuners / Receivers / Audio Tape Players / MINI Systems / Misc. / HTIB / Web & Computer TV / Scart Switch Boxes / Digital Set Top Boxes / Misc. Set Top Boxes / Media Receivers / Picture Frame / Media Center PC / Home Auto-mation / Entertainment Box / Video On Demand
CD	CD / LD
HD	HDD-DVR
DVR	DVR / VCR

※ **Suggerimenti:**

Quando è necessario controllare altri dispositivi non specificati in questo pannello di controllo a distanza, e' possibile inserire il codice di un altro dispositivo su qualsiasi tasti del dispositivo, dopo l'installazione, e' possibile controllare gli altri tipi di dispositivi di cui sopra.

Per esempio:

Nel dispositivo "TV", inserire il codice "VCR" della lista, dopo l'installazione, con Forma A, e' possibile controllare il dispositivo "VCR" nel "TV", e così successivamente.

- Questa installazione corrisponde solo al metodo di un codice di mano con Forma A.
- Se si utilizza il metodo di installazione B / C, si può trovare solo i tipi di dispositivi all'interno delle chiavi, vuol dire che il metodo di installazione B/C senza i tasti di dispositivo non e' supportato.

< Lo schema del telecomando e' solo un punto di riferimento per l'installazione, si prega di vedere il prodotto reale >

DVD / VCR (COMBOS)

DVD-VCR combos operate with either a single DVD code or some require both DVD & VCR codes.

HOW TO SET LEARN FUNCTION

1. Press the category key of the equipment you want to learn (such as **TV**, SAT, DVD), and the indicator light will twinkle once
2. Press on the "SETUP"(**SET**) key until the indicator light lights and keeps shining
3. Press the "**LEARN**" key, and the indicator light will twinkle once (or input the code **9980**)
4. Press the keys of this remote control you want to learn (except the device category key, SETUP, LEARN), such as **power** key, and the indicator light will twinkle once
5. Lie flat the original remote control (the remote control to be learned) and this remote control, and align the infrared emission window of the two remote controls and keep the distance between them being 2-5CM; press the corresponding key of the original remote control, such as the **power** supply key, and the indicator light will keep on shining after quenching for 1-3 sec. If your learning is not successful, then the indicator light will twinkle for three sec and keeps shining, and you may continue to learning other keys
6. Repeat the procedure 5 to learn other keys, and when you finish your learning, press "SETUP"(**SET**) key to exit the learning mode

! Warm tip

Learning Function only work for some models.If there is not "Learn" key on the remote control or the indicator light has no reponse after entering code "9980",then this remote control is without learning function.

HOW TO USE COMBINED EQUIPMENTS

This is related with the equipments brands and the combined equipments (TV/VCR, DVD/VCR etc.) types, for some of them, it will be ok to input one code, while for others, it requires to input two codes respectively for two different equipment keys; refer to the code list for detail.

1. Manually turn on the combined equipments you want to control.
2. Find out the code that may control the equipment in the code inputting way, manual searching way or automatic searching way according to the above hint.
3. If you can't control the other equipment, then repeat procedure 2

SEARCHING FOR THE CURRENT CODE

After the manual searching or the automatic searching is successful, if you want to know the code that controls your household appliances, please operate according to the following procedures:

DVB-T

DVB-T Terrestial Digital Television (DTV. Freeview. IDTV. etc)

B MANUALLY SEARCH FOR THE CORRESPONDING CODE

1. Turn on the household appliances you want to control (such as TV, STB, DVD).
2. Press the device category key (such as **TV**, SAT, DVD), and the indicator light will twinkle once
3. Press on the "SETUP"(**SET**) key until the indicator light lights and keeps shining
4. Point the remote control towards the infrared reception window of the equipment you're going to control, and press on "**CH+**"(P+) key at certain intervals (with the interval being less than 1.5s, or the remote control will enter into the automatic searching mode) until the channel of the equipment changes, then you should loose the "CH+"(P+) key at once, and press "**OK**" key to exit the searching mode.

Attention: If the equipment doesn't have "CH+"(P+) function, you may use the "**PLAY**" key or the "**POWER**" key instead, and when the equipment's status begin to change, press "OK" key to exit.

5. Check whether every function keys of the remote control work normally, if it does, the setting is successful; if not, please repeat procedure 3-4.

Picture Frame

AUX

Audio Amplifiers . Tuners . Receivers

INSTRUCTIONS

English

Thank you for choosing this product. After correctly setting, the remote will support the following categories of devices:

Device key	Categories of devices covered
TV	TV / DTV Receiver / TDT
SAT	SAT / Decoder Cable / DVB-T
DVD	DVD / DVD-R
AUX	AUX / Audio / Amplifiers / Tuners / Receivers / Audio Tape Players / MINI Systems / Misc. / HTIB / Web & Computer TV / Scart Switch Boxes / Digital Set Top Boxes / Misc. Set Top Boxes / Media Receivers / Picture Frame / Media Center PC / Home Auto-mation / Entertainment Box / Video On Demand
CD	CD / LD
HD	HDD-DVR
DVR	DVR / VCR

※ **Warm tip**

To control other devices not present on the panel of the remote, press any key to enter code of the device, and the device will be controllable with the remote.

Example:

For "TV" device, enter the codes of "VCR" from the code list, follow the setting method A, then "VCR" device can be controlled with the remote under "TV" mode.

- This operation is only for setting method "**A.MANUALLY INPUT THE CONRRESPONDING CODE**".
- Using setting method **B/C** just can search the devices metiond above. It cannot be used for the devices without the devices button.

< The remote control picture shown in the manual is only for setting reference, detailed information is in accordance with the final product. >

Media Center PC

MCE	1100
MICROSOFT	1100
VISTA	1100

Home Auto mation

HOME AUTOMATION	0998
LUTRON	0887
X-10 HOME AUTOMATION	0998